

What You Need To Do

**(National Fire Protection Association [NFPA], @ NFPA 110 Standard for Emergency and Standby Power Systems, 2010 Edition*

Set up a routine maintenance and testing schedule. (*NFPA 110 8.3.3)

Keep good written records of all inspections, tests, repairs, and maintenance. (*NFPA 110 8.3.4)

Test entire system for 30 minutes after any repair or service. (*NFPA 8.3.2.1)

Weekly:

- Inspect the generator. (*NFPA 110 8.4.1)
- Check the oil, fuel, and coolant
- Make sure the heater is working
- Check the battery

Monthly:

- Run **diesel** generators **at 30%** of its rated load at minimum of 30 minutes. Gas generators need not reach 30% load but must be tested for 30 minutes per month. (*NFPA 110 8.4.2 & 8.4.2.4)
- Record oil pressure, engine temperature, and AC amperage.
- Transfer **all** transfer switches to the Generator. Include the fire pump transfer switch. (*NFPA 110 8.4.6.1 & *NFPA 25 8.3.4.2)

Annually:

- Test the generator and fire pump together at full load. (*NFPA 25 8.3.3.4)
- Operate the generator breaker. *(NFPA 110 8.4.7)
- Test **diesel** fuel annually. (*NFPA 110 8.3.8)

Every Three Years:

- Test system under load for 4 hours

Standby Power Solutions LLC.

Generator Services Inc disclaims any liability for any personal injury, property, or other damages of any nature whatsoever, whether special, indirect, consequential, or compensatory, directly, or indirectly resulting from the publication, use of, or reliance on this document. Generator Services Inc also makes no guarantee or warranty as to the accuracy or completeness of any information contain herein. Anyone using this document should rely on his or her own independent judgment, or as appropriate, seek the advice of a competent professional in determining he exercise of reasonable care in given circumstances.

©2020 by Standby Power Solutions LLC. All rights reserved. Do not reproduce without express written permission.

